

Description

The Store may be used as a backup for a main show controller, so that, in the event that the main controller crashes or loses power, the operator still has 64 pre-programmed lighting scenes at his disposal while the main system is being brought back on line.

It is equally valuable as a stand-alone controller in many less-demanding applications where there is little justification for tying up larger, more expensive desks, for example museum exhibits, retail sites, exhibition stands, static displays.

Where a fully automatic use is required, the Store may be set up to take control when power is applied and to start processing commands without any user intervention.

A reassuring feature of the Store is its memory card slot. Programming may be saved to a PCMCIA card for safe keeping in a few seconds and restored just as easily.



Key Features

- Store up to 64 scenes of 512 channels of DMX information
- Edit fade and hold times
- Combine scenes into repeating loops
- Play back scenes from front panel switch/slider or remote switches
- Use to back up main show controller or as stand-alone playback unit

Technical Specifications

Power Supply	220 - 240VAC 50/60Hz 100 - 120VAC 50/60Hz version available to order
Lighting Channels	512
Control Channels	6-Binary address, 6-Control functions
Memory	64 Scenes of all 512 channels
Back-up	PCMCIA card (available option)
Signal Input (Lighting)	USITT DMX512 via XLR 5pin
Signal Input (Control)	3-10V dc via 25 pin computer 'D' type
Signal Output (Lighting)	USITT DMX512 via XLR 5pin
Signal Output (Control)	Nominal 12V dc " 30mA max



Weight: 3.5kg

Dimensions 45 x 485 x 165mm